

## ABNORMAL TEST RESULT

OF MODEL LDA150W

1. Did Cheese Cloth or Paper Glow?

No.

2. Did Ground Fuse Open?

No.

3. Dielectric breakdown?

No.

4. Other Results?

See the following pages (1/3~3/3).

There was no emission of flame, molten metal, ignition of cheesecloth, dielectric breakdown, opening of the ground fuse, other indication of a shock or fire hazard.

ABNORMAL TEST RESULT

Component	Mode	Comment	Output Voltage (V)
C104	Short	F11 opened, No Hazard.	0V
C107	Short	F11 opened, No Hazard.	0V
	Open	Output voltage decreased. No Hazard.	
C108	Short	F11 opened, No Hazard.	0V
	Open	Output voltage decreased. No Hazard.	
C151	Open	Normal operation.	
C153	Open	Normal operation.	
C203	Open	Output voltage decreased. No Hazard.	
IC151 ①	Open	F11 opened, No Hazard.	0V
IC151 ⑥	Open	Output voltage decreased.	
		No Hazard.	
IC151 ⑧	Open	Output voltage decreased.	
		No Hazard.	
IC201 ②	Open	F11 opened, No Hazard.	0V
IC201 ③	Open	Normal operation.	
IC201 ⑫	Open	Output voltage decreased.	
		No Hazard.	
IC201 ⑬	Open	Output voltage decreased.	
		No Hazard.	
IC201 ①-②	Short	F11 opened, No Hazard.	0V
PC101 T1-T2	Short	F11 opened, No Hazard.	0V
R156	Open	F11 opened, No Hazard.	0V
R157	Open	Normal operation.	

## ABNORMAL TEST RESULT

Component	Mode	Comment	Output Voltage (V)
R158	Open	Normal operation.	
R161	Open	F11 opened, No Hazard.	0V
R203	Open	Output voltage decreased. No Hazard.	
R212	Open	F11 opened, No Hazard.	0V
TRC101 T1-T2	Short	F11 opened, No Hazard.	0V
TRC101 T1-G	Short	Normal operation.	
TRC101 T2-G	Short	F11 opened, No Hazard.	0V
TR151 D-S	Short	Normal operation.	
TR151 S-G	Short	Normal operation.	
TR152 C-E	Short	F11 opened, No Hazard.	0V
TR152 B-C	Short	F11 opened, No Hazard.	0V
TR201 C-E	Short	Normal operation.	
TR202 D-S	Short	F11 opened, No Hazard.	0V
TR202 G-S	Short	No Hazard.	0V
TR202 G-D	Short	F11 opened, No Hazard.	0V
TR202 D	Open	No Hazard.	0V
TR202 S	Open	No Hazard.	0V
TR202 G	Open	F11 opened, No Hazard.	0V
ZD151	Open	Normal operation.	
D153	Short	Normal operation.	
D151	Open	F11 opened, No Hazard.	0V
L505	Open		