

Temperature increase of main components

Model: SUS/SUW324

## 1. Conditions

- (1) Input :DC 18 - 36 [V]  
 (2) Output :Rated output  
 (3) Cooling method :Convection cooling  
 (4) Mounting method :Shown as Fig.1.1

## 2. Result

Table 2.1 Temperature increase of main components

Table 2.1 Temperature increase of main components										
No.	Parts name	Symbol No.	Increase ( $\Delta T$ )						Rated temp. [°C]	Reference
			[deg]							
			3.3V	5V	12V	15V	±12V	±15V		
1	Transformer	T11	38	54	52	51	49	49	155	
2	Switching Transistor	TR11	35	43	40	35	36	36	150	Junction temp.
3	Rectified Diode(Output)	D51	39	47	47	43	-	-	150	Junction temp.
4	Rectified Diode(Output)	D52	-	-	-	-	44	40	150	Junction temp.
5	Input Choke	L11	26	34	34	31	28	31	130	
6	Output Choke	L51	24	28	26	26	-	-	130	
7	Output Choke	L52	-	-	-	-	32	28	125	
8	Photocoupler	PC11	35	41	41	39	38	40	125	Junction temp.
9										
10										
11										
12										
13										
14										
15										
16										
17										
18										
19										
20										



(Side view)

Fig.1.1 Mounting method  
(Normal position)