

Date : Apr 11,2005

Temperature increase of main components

Model: SUS/SUW305

1. Conditions

- (1) Input :DC 4.5 - 9 [V]
 (2) Output :Rated output
 (3) Cooling method :Convection cooling
 (4) Mounting method :Shown as Fig.1.1

2. Result

Table 2.1 Temperature increase of main components

Table 2.1 Temperature increase of main components										
No.	Parts name	Symbol No.	Increase (ΔT)						Rated temp. [°C]	Reference
			[deg]							
			3.3V	5V	12V	15V	$\pm 12V$	$\pm 15V$		
1	Transformer	T11	41	58	49	52	57	52	155	
2	Switching Transistor	TR11	38	61	52	54	55	53	150	Junction temp.
3	Rectified Diode(Output)	D51	38	46	46	43	-	-	150	Junction temp.
4	Rectified Diode(Output)	D52	-	-	-	-	47	44	150	Junction temp.
5	Input Choke	L11	27	40	37	39	39	37	130	
6	Output Choke	L51	22	28	26	26	-	-	130	
7	Output Choke	L52	-	-	-	-	35	33	125	
8	Photocoupler	PC11	35	40	39	42	41	44	125	Junction temp.
9										
10										
11										
12										
13										
14										
15										
16										
17										
18										
19										
20										



(Side view)

Fig.1.1 Mounting method
(Normal position)