



TEST DATA OF TSC-400-□□□-H

Noise Filter

Sep. 02 , 2021

Approved by : Kazunari Asano
Design Manager

Prepared by : Kenji Kamoi
Design Engineer



COSEL CO.,LTD.

CONTENTS

1.Attenuation Characteristics	1
2.Leakage Current	3
3.Figure of Testing Circuitry	4
(Final Page 5)	





Model		TSC-400-□□□-H	Temperature 25°C Testing Circuitry Figure A
Item		Attenuation Characteristics	
Object		_____	





Model		TSC-400-□□□-H	Temperature 25°C Testing Circuitry Figure A
Item		Attenuation Characteristics	
Object		_____	





Model		TSC-400-□□□-H	Temperature 25°C Testing Circuitry Figure B
Item		Leakage Current	
Object		_____	

1.Results

[mA]

Model	Standards	Voltage system	Input Volt.					Note
			200[V]	250[V]	400[V]	480[V]	500[V]	
TSC-400-000-H	UL1283	Δ-connection	0.01	0.02	0.03	0.03	0.04	
		Y-connection	0.00	0.00	0.00	0.00	0.00	
TSC-400-304-H	UL1283	Δ-connection	6.2	8.0	13	15	16	
		Y-connection	0.01	0.01	0.02	0.03	0.03	
TSC-400-664-H	UL1283	Δ-connection	13	17	27	32	34	
		Y-connection	0.02	0.03	0.04	0.05	0.05	
TSC-400-665-H	UL1283	Δ-connection	64	80	128			Δ-connection's rated voltage is 400V(440Vmax)
		Y-connection	0.22	0.27	0.44	0.52	0.55	

2.Condition

Leakage current value is concluded after measuring both phases of AC input and by choosing the larger one.




Figure A - 1 Differential mode attenuation measurement




Figure A - 2 Common mode attenuation measurement




Figure B - 1 Leakage current measurement (UL1283 Δ-connection)




Figure B - 2 Leakage current measurement (UL1283 Y-connection)